


## Povezivanje na mrežu

DE-Ic funkcija




<b>Rated voltage</b>	Ur	kV	12	17.5	24						
<b>Rated frequency</b>	Fr	Hz	50 or 60	50 or 60	50 or 60						
<b>Insulation level</b>											
Industrial frequency 50Hz/1min	Phase-to-phase, phase-to-earth	Ud	kV rms	28	38	50					
	Across isolating distance Ud		kV rms	32	45	60					
Lightning impulse withstand	Phase-to-phase, phase-to-earth	Up	kV peak	75	95	125					
	Across isolating distance Up		kV peak	85	110	145					
<b>Rated current</b>	Ir	A	200	630	200	630	200	630	200	200	200
<b>Rated current busbars</b>	Ir	A	630	630	630	630	400	400	630		
<b>Short-time withstand current</b>	It	kA rms	25	21 <sup>(1)</sup>	16	20	12.5	16	12.5		
	tk	s	1	1 or 3	1	1 or 3	1	1	1		
<b>No-load transformer breaking capacity</b>	I3	A	-	16	-	16	-	16	16	16	16
<b>Short-circuit breaking capacity</b>	Isc	kA	25	21	16	20	12.5	16	12.5		
<b>Making capacity</b>	I <sub>ma</sub>	kA peak	62.5	52.5	40	50	31.25	40	31.25		
<b>Operating sequence</b>			O – 3min- CO – 3min - O								
<b>Bushing<sup>(2)</sup></b>			Type	C	C	C	C	A	BorC	A	
<b>Mechanical endurance</b>	Circuit breaker	M1	Number of openings	2000	2000	2000					
	Earthing switch	M0	Number of openings	1000	1000	1000					
<b>Electrical endurance</b>	Circuit breaker	E2	Number of short-circuit breaking operations	3	3	3					
			Number of short-circuit making operations	2	2	2					
	Earthing switch	E2	Number of CO at rated current	100	100	100					
			Number of short-circuit making operations	5	5	5	2	5	5	5	

(1) 17.5 kA for DE-Bc

(2) No bushing for DE-Bc function

## Povezivanje na mrežu



DE-IC

### Dodatni pribor i opcije

#### Daljinske operacije

Motorni mehanizam i pomoćni kontakti LBSw 2 NO - 2 NC i ESsw 1 O/C (uključujući i paralelni kalem za okidanje).

#### Pomoćni kontakti

Za indicaciju položaja glavnog rastavljača 2 NO - 2 NC i ESsw 1 O/C (ova opcija postoji i kod daljinskih operacija).

#### Prednja prilazna vrata za postojeće senzore

- Zašrafljena
- Sa mogućnošću otvaranja sa ESsw blokadom
- Sa mogućnošću otvaranja sa ESsw blokadom i LBSw blokadom.

#### Uređaj za odvođenje električnog luka

#### Bez prekidača za uzemljenje

#### Brave

- Tip R1
- Tip R2.